

# VDC5 Bell End Anchor

Fittings › Product 16603

## Description

This fitting anchors VDC5 into a hand hole or enclosure. The fitting also creates a smooth end transition into the VDC5 conduit.

## Applications

The fitting is ideal for FTTH and FTTB applications. The system works well with flat aerial drop cables.

## Features/Benefits

- Anchors the VDC5 conduit into a vault or handhole
- The fitting is split to allow cables to be inlaid in
- Creates a smooth transition with no sharp edges into the VDC5 conduit
- The fitting mounts flush to the inside walls of the vault or handhole
- Can be installed using a standard hole saw (3.75" bit)
- Can be fixed to a vault or handhole by using a compression ring or by simply screwing the square flange into the body of the vault or handhole

## Specifications

- Assembly weight --- 255 grams (0.56lbs)

### Installed Dimensions

- Square flange size --- 140mm x 140mm (5.5"x5.5")
- Body diameter --- 95mm (3.75")
- Body depth --- 80mm (3.15")

### Material

- Body --- 10% glass filled nylon
- Fastener --- Stainless Steel

### Tools Required for Assembly

- Philips screw driver
- 3.75" hole saw

